


**250** psi rating pneumatic

**1500** psi rating hydraulic

# series L

## pneumatic cylinders



**ROYAL**  
by Westcoast Cylinders Inc.

**Page Description**

- 1 Mounting Styles  
 2 Features Description  
 3 Features Drawing


**Mounting dimensions**

- 4 C Fixed Clevis (MP1)  
 4 E Pivot Eye (MP3)  
 5 F Foot Mount (MS2)  
 6 MP Detachable Blind-end Clevis (MP-2)  
 6 W Self-aligning Eye (MPU3)  
 7 NM No Mount (MX0)  
 7 NA Extended Tie-rods Both Ends (MX1)  
 8 NB Extended Tie-rods Blind End (MX2)  
 8 NC Extended Tie-rods Gland End (MX3)  
 9 R Rod End Rectangular Flange (MF1)  
 9 RS Rod End Square Flange (MF5)  
 10 B Blind End Rectangular Flange (MF2)  
 10 BS Blind End Square Flange (MF6)  
 11 TR Rod End Trunnion (MT1)  
 11 TB Blind End Trunnion (MT2)  
 12 D Double Rod (MD)  
 12 T Mid Trunnion (MT4)  
 13 CH Common Head  
 13 CR Common Rod  
 14 CHR Common Head / Common Rod


15-17 Rod End Styles, Accessories

**Parts**


- 18 Parts List: 1.5 – 6" dia.  
 19 Parts Drawing  
 20 Parts List: 8 – 12" dia.  
*Pressure Rating Table*  
 21 Technical Data

**Cylinder Nomenclature****Westcoast Cylinders Inc.**


225 Edworthy Way  
 New Westminster BC  
 Canada V3L 5G4  
 Telephone: 604 527 1120  
 Facsimile: 604 527 1170  
 Phone Toll Free: 1 877 637 6925  
 Fax Toll Free: 1 866 527 1170  
 email: sales@royalcylinders.com  
 website: www.royalcylinders.com




**8** Extended Tie-rods Gland End




**10** Blind End Square Flange




**12** Mid Trunnion




**9** Rod End Rectangular Flange




**11** Rod End Trunnion




**13** Common Head




**9** Rod End Square Flange




**11** Blind End Trunnion




**13** Common Rod



**10** Blind End Rectangular Flange



**12** Double Rod



**14** Common Head/Common Rod

#### Westcoast Cylinders Inc.:

The company has been manufacturing high quality, reliable ROYAL cylinders for over 40 years. Production started with a single cylinder design and expanded to a full range of multi-use, hydraulic, pneumatic cylinders and accessories.

#### Quality:

WCI is a leader in the design and manufacture of custom heavy duty cylinders. The materials, machinery and tools used to produce our products are continuously being updated. Our cylinders are built to the highest standards utilizing the latest technology and processes.

#### Delivery:

WCI maintains a large range of stock parts which gives us the flexibility to respond to your needs in emergency situations. Please contact our factory to expedite your special requirements.

## NFPA STANDARD MOUNTS

All mountings are NFPA compliant and can be interchanged with other cylinders meeting NFPA standards.

## NITROTEC TREATED MATERIALS

**Nitrotec** is a patented furnace treatment process which converts the steel surface into an extremely hard black iron nitride layer. It is superior to chrome plating in that the nitriding is diffused into the steel surface rendering the surface nonporous. There is no flaking or lifting as with overlying chrome on a softer material.

**Nitrotec** delivers an exceptional surface hardness of up to 71 Rc, improves corrosion resistance and minimizes friction loss for long seal and gland bushing life.

The **Nitrotec** process also gives an extremely hard dent-resistant finish to materials. Beneath the outer surface is a diffusion zone which gradually reduces in hardness to approximately 40 Rc at 0.015" depth. This diffusion zone acts as a **case-hardening** which is much superior to the relatively soft material underlying chrome plate.

### Nitrotec Piston Rod

The piston rod is **Nitrotec** treated C1045 carbon steel. Other rod materials are available including chrome plated 316 stainless steel and chrome plated carbon steel. If you require a rod size that is not included in this catalog contact the factory for information regarding availability and dimensions.

### Nitrotec Barrel

**Nitrotec** treated steel is the standard barrel material. Other barrel materials are available upon request including chromed I.D. steel, Brass and Amalgan.

## TEFLON® / HYTHANE® SEALS

The piston seal is a double acting **Teflon®** impregnated compound to reduce friction yet enhance seal life. It has an exceptional temperature range of from -40 to 275°F. The **Hythane®\*** rod seal is a high performance, high temperature seal compound having ultra low friction and long seal life. Its temperature range is from -40 to 230°F. The **Hythane®** rod wiper, with internal ribs for extra stability and prevention of pressure trapping, cleans the rod on the return stroke. The static external seal is Buna-N material.

## ROTOCAST BRONZE GLAND BUSHING

The gland bushing is manufactured from Rotocast bronze for low friction and long bearing life. Other materials such as Zincaloy are available upon request. A snap ring retainer allows for easy removal of the bushing for maintenance without dismantling the cylinder. Optional gland bushings with wear rings may be available, contact the factory.

## COLD FINISHED HEADS

Heads are precision machined from high quality cold finished steel for perfect alignment of barrel and moving parts. For the 1½" bore and all bores 3¼" and larger, the heads are common for all rod sizes. This allows the end user to lower costs by stocking only one head for all rod sizes. The common head design also enables customers to increase or decrease rod sizes with little effort or expense. Due to space constraints on the 2" bore, the heads are

common between the 1" and 1¾" rod sizes only. On the 2½" bore the heads are common only on the 5/8" and 1" rod sizes.

## IMPROVED CUSHIONING:

### Floating Check Seals

Cushions are now standard in our pneumatic cylinders. They have been redesigned with a new floating check seal that provides quick and reliable breakaway performance. They are made from the same long wearing **Hythane®** material.

### Lengthened Cushion Sleeves

Our cushion sleeves have been lengthened with a new profile to provide a more effective cushion. On some of the smaller sizes that cannot fit a floating check seal, the cushion sleeve itself is floating. This eliminates the possibility of metal "pick-up" and premature wear. In addition, this floating sleeve has a locational-memory feature which centers the sleeve after the first cylinder cycle and holds its position thereafter to eliminate wear from repeated radial displacement.

### Flush Mount Needle Valves

Needle valves are now the flush mount style and allow a fine adjustment. The standard location is at position 4, but they can be specified elsewhere. Contact the factory for cushioning options on the gland end of the 1½" bore (both rod sizes), and the 2" bore (1" and 1¾" only rod sizes).

## CONVERTING TO NON-CUSHIONED

All heads are manufactured with integral cushion features making a conversion from a cushioned to a non-cushioned cylinder a simple, inexpensive process. To convert to a non-cushioned cylinder simply remove the check seal. If no check seal exists, as on the rod end of some smaller bore sizes, remove the cushion sleeve.

## ONE-PIECE ALUMINUM PISTON

The piston is a one-piece design, aluminum construction, incorporating a replaceable wear ring to prevent metal to metal contact and increase the life of the cylinder.

## NPTF / SAE PORTS

NPTF ports are standard at position 1 but can be specified in other positions. SAE straight thread O-ring ports are available at no additional cost.

## REDUCED AIR PRESSURE REQUIREMENTS

The combination of seals and materials used within Royal air cylinders reduces internal friction thus reducing air pressure requirements. Reducing air pressure lowers consumption costs. Testimonials from customers show a reduction in pressure from 10 to 30%.

## INTERNAL / EXTERNAL PISTON STOP

Standard external or optional internal piston stops are available to reduce stress on the piston rod for all cylinder sizes.

## STROKE POSITION SENSORS

Proximity sensors or other switches can be fitted in most models. Contact the factory for details.


## CUSTOM CYLINDERS


If our standard product does not meet your specifications, Westcoast Cylinders will manufacture custom cylinders to meet your requirements. Please contact the factory.

## SPARE PARTS

Genuine Royal seal kits include all seal components, wear rings and needle valves. Please ensure to specify genuine Royal replacement parts to ensure you will receive all feature benefits.





\* Hythane® is a registered trademark of Hallite Seals International Ltd.








model LC, LE

ROD DIA.		+ STR								LC		LE		EE									
BORE	ROD	MM	KK	CC	A	WF	V	B	XC	E	G	J	L	CB	CB	CD	CW	NPTF	SAE	MR	XX		
<b>1 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	3/4	1 11/16	5 3/8	2	1	3/16	15/16	3/4	25/32	3/4	1/2	1/2	3/8	-	1/2	1/4	
	2	1	3/4-16	7/8-14	1 1/8	1	3/8		5 3/8	2 1/2	1	3/16	15/16	3/4	25/32	3/4	1/2	1/2	3/8	-	1/2	5/16	
<b>2</b>	1	5/8	7/16-20	1/2-20	3/4	1	3/4	2 7/32	5 3/8														
	2	1	3/4-16	7/8-14	1 1/8	1	3/8		5 3/4														
<b>2 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	13/16	2 5/16	5 1/2	3	1	1 1/4	1	3/4	25/32	3/4	1/2	1/2	3/8	-	1/2	5/16	
	2	1	3/4-16	7/8-14	1 1/8	1	3/8		5 7/8														
<b>3 1/4</b>	3	1 3/8	1-14	1 1/4-12	1 5/8	1	5/8		6														
	1	5/8	7/16-20	1/2-20	3/4	1	13/16	2 5/16	5 1/2	3	1	1 1/4	1	3/4	25/32	3/4	1/2	1/2	3/8	-	1/2	5/16	
<b>3</b>	1	3/8	1-14	1 1/4-12	1 5/8	1	5/8		6	7/8	3	3/4	1 11/32	1 7/32	1 1/4	1 9/32	1 1/4	3/4	5/8	1/2	-	3/4	3/8
	2	1 3/8	1-14	1 1/4-12	1 5/8	1	5/8		7 1/8														
<b>4</b>	3	1 3/4	1 1/4-12	1 1/2-12	2	1	7/8		7 3/8														
	1	1	3/4-16	7/8-14	1 1/8	1	3/8	15/16	3 1/4	6 7/8	4	1/2	1 3/8	1 1/8	1 1/4	1 9/32	1 1/4	3/4	5/8	1/2	-	3/4	3/8
<b>5</b>	2	1 3/8	1-14	1 1/4-12	1 5/8	1	5/8		7 3/8														
	3	1 3/4	1 1/4-12	1 1/2-12	2	1	7/8		7 5/8														
<b>6</b>	1	1 3/8	1-14	1 1/4-12	1 5/8	1	5/8	1	8 1/8	6 1/2	1	5/8	1 3/8	1 1/4	1 1/4	1 9/32	1 1/4	3/4	5/8	1/2	-	3/4	1/2
	2	1 3/4	1 1/4-12	1 1/2-12	2	1	7/8		8 3/8														
<b>8</b>	3	2	1 1/2-12	1 3/4-12	2 1/4	2			8 1/2	8 1/2	1	5/8	1 3/8	1 1/2		1 9/16	1 1/2	1	3/4	3/4	-	1	5/8
	1	1 3/8	1-14	1 1/4-12	1 5/8	1	5/8	5/8	8 5/8														
<b>10</b>	2	1 3/4	1 1/4-12	1 1/2-12	2	1	7/8	6 3/8	10 3/8	10 5/8	2	1	3/4	2 1/8		2 1/16	2	1 3/8	1	1	-	1 3/8	3/4
	3	2 1/2	1 7/8-12	2 1/4-12	3	2	1/4		10 3/4														
<b>12</b>	1	2	1 1/2-12	1 3/4-12	2 1/4	2		7/8	6 3/4	11 1/8	12 3/4	2	1 5/8	2 1/4		2 9/16	2 1/2	1 3/4	1 1/4	1	-	1 3/4	3/4
	2	2 1/2	1 7/8-12	2 1/4-12	3	2	1/4		11 3/8														
	3	3	2 1/4-12	2 3/4-12	3 1/2	2	1/4		11 3/8														

Model LC  
NFPA Style MP1Model LE  
NFPA Style MP3




ROD DIA.										+ STR	EE		NPTF SAE	SB	ST	SU	SW	TS	US	XX										
BORE	ROD	MM	KK	CC	A	WF	B	V	XS	SS	E	G	J	SS	ST	SU	SW	TS	US	XX										
<b>1 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	1	11/16	3/4	1	3/8	2	7/8	2	1	3/16	15/16	3/8	-	13/32	3/8	15/16	3/8	2	3/4	3	1/2	1/4		
	2	1	3/4-16	7/8-14	1	1/8	1	3/8			1	3/4																		
<b>2</b>	2	1	3/4-16	7/8-14	1	1/8	1	3/8			1	3/4																		
	3	1	3/8	1-14	1	1/4-12	1	5/8	1	5/8		2																5/16		
<b>2 1/2</b>	2	1	3/4-16	7/8-14	1	1/8	1	3/8			1	3/4																		
	3	1	3/8	1-14	1	1/4-12	1	5/8	1	5/8		2																		
<b>3 1/4</b>	1	1	3/4-16	7/8-14	1	1/8	1	3/8	2	7/8	15/16	1	7/8																	
	2	1	3/8	1-14	1	1/4-12	1	5/8	1	5/8		2	1/8																	
<b>4</b>	3	1	3/4	1 1/4-12	1	1 1/2-12	2	1	7/8		2	3/8																		
	1	1	3/4-16	7/8-14	1	1/8	1	3/8	3	1/4	15/16	1	7/8																	
<b>5</b>	2	1	3/8	1-14	1	1/4-12	1	5/8	1	5/8		2	5/16																	
	3	1	3/4	1 1/4-12	1	1 1/2-12	2	1	7/8		2	9/16																		
<b>6</b>	1	1	3/8	1-14	1	1/4-12	1	5/8	1	5/8	4	1/2	1	2	5/16															
	2	1	3/4	1 1/4-12	1	1 1/2-12	2	1	7/8		2	9/16																		
<b>8</b>	3	2	1 1/2-12	1 3/4-12	2	1/4	2				2	11/16																		
	1	1	3/8	1-14	1	1/4-12	1	5/8	1	5/8	5	3/4	5/8	2	5/16															
<b>10</b>	2	1	3/4	1 1/4-12	1	1 1/2-12	2	1	7/8	6	3/8	7/8	2	3/4																
	3	2	1/2	1 7/8-12	2	1 1/4-12	3	2	1/4			3	1/8																	
<b>12</b>	1	2	1 1/2-12	1 3/4-12	2	1/4	2		6	3/4	7/8	2	7/8																	
	2	2	1/2	1 7/8-12	2	1 1/4-12	3	2	1/4			3	1/8																	
	3	3	2 1/4-12	2 3/4-12	3	1/2	2	1/4			3	1/8																		







Model LF  
NFPA Style MS2

**Note:**


For 1 1/2" bore cushioned foot mount cylinder - due to the position of the needle valve, installer should pre-adjust before cylinder is mounted.

model **LMP, LW**



ROD DIA.										+ STR		+ STR												EE						
BORE	ROD	MM	KK	CC	A	WF	V	B	XD	XH	E	F	G	J	L	CB	CK	CD	CW	NPTF	SAE	MA	MR	SL	XX					
<b>1 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	3/4	11 1/16	5 3/4	5 7/16	2	3/8	1 3/16	15/16	3/4	0.76	7/16	1/2	1/2	3/8	-	3/4	5/8	13/16	5/16					
	2	1	3/4-16	7/8-14	1 1/8	1	3/8		6 1/8	5 13/16										3/8	-	3/4	5/8	13/16	5/16					
<b>2</b>	1	5/8	7/16-20	1/2-20	3/4	1	3/4	2 7/32	5 3/4	5 7/16	2 1/2	3/8	1 3/16	15/16	3/4	0.76	7/16	1/2	1/2	3/8	-	3/4	5/8	13/16	5/16					
	2	1	3/4-16	7/8-14	1 1/8	1	3/8		6 1/8	5 13/16										3/8	-	3/4	5/8	13/16	5/16					
<b>2 1/2</b>	1	3/8	1-14	1 1/4-12	1 5/8	1	5/8		6 3/8	6 1/16										3/8	-	3/4	5/8	13/16	5/16					
	2	1	3/4-16	7/8-14	1 1/8	1	3/8	15/16	2 7/8	7 1/2	6 13/16	3 3/4	3/8	1 1/4	1	3/4	0.76	7/16	1/2	1/2	3/8	-	3/4	5/8	13/16	5/16				
<b>3 1/4</b>	1	3/8	1-14	1 1/4-12	1 5/8	1	5/8		7 3/4	7 1/16										1/2	-	1 1/4	7/8	1 3/16	3/8					
	2	1	3/8	1-14	1 1/4-12	1 5/8	1	5/8	8	7 5/16										1/2	-	1 1/4	7/8	1 3/16	3/8					
<b>4</b>	1	1	3/4-16	7/8-14	1 1/8	1	3/8	15/16	3 1/4	7 1/2	6 13/16	4 1/2	5/8	1 3/8	1 1/8	1 1/4	126	21/32	3/4	5/8	1/2	-	1 1/4	7/8	1 3/16	3/8				
	2	1	3/8	1-14	1 1/4-12	1 5/8	1	5/8	7 3/4	7 1/16										1/2	-	1 1/4	7/8	1 3/16	3/8					
<b>5</b>	3	1/4	1 1/4-12	1 1/2-12	2	1	7/8		8	7 5/16										1/2	-	1 1/4	7/8	1 3/16	3/8					
	1	1	3/4-16	7/8-14	1 1/8	1	3/8	15/16	3 3/4	7 3/4	7 1/16	5 1/2	5/8	1 3/8	1 1/4	1 1/4	126	21/32	3/4	5/8	1/2	-	1 1/4	7/8	1 3/16	3/8				
<b>6</b>	2	1	3/8	1-14	1 1/4-12	1 5/8	1	5/8	8	7 9/16										1/2	-	1 1/2	1 1/8	1 9/16	1/2					
	3	2	1-14	1 1/4-12	1 1/2-12	2	1	7/8	9 1/8	8 7/16										3/4	-	1 1/2	1 1/8	1 9/16	1/2					
									9 1/4	8 9/16																				

Model **LMP**  
NFPA Style MP-2Model **LW**  
NFPA Style MPU3



## model LNM, LNA



ROD DIA.													+ STR		EE										
BORE	ROD	MM	KK	CC	A	WF	W	V	B	AA	BB	DD	ZJ	E	F	G	J	K	R	NPTF	SAE	XX			
<b>1 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	5/8	3/4	1 11/16	2.02	1	1/4-28	4 5/8	2	3/8	1	3/16	15/16	5/16	1.43	3/8	-	1/4		
	2	1	3/4-16	7/8-14	1 1/8	1	3/8	1					5												
<b>2</b>	1	5/8	7/16-20	1/2-20	3/4	1	5/8	3/4	2 7/32	2.60	1	1/8	5/16-24	4 5/8	2 1/2	3/8	1	3/16	15/16	3/8	1.84	3/8	-	5/16	
	2	1	3/4-16	7/8-14	1 1/8	1	3/8	1					5												
<b>2 1/2</b>	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1 1/4				5 1/4												
	2	1	3/4-16	7/8-14	1 1/8	1	3/8	1	5/8	13/16	2 5/16	3.10	1 1/8	5/16-24	4 3/4	3	3/8	1 1/4	1	3/8	2.19	3/8	-	5/16	
<b>3 1/4</b>	1	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1 1/4			5 1/8												
	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1 1/4			5 3/8												
<b>3 1/2</b>	1	1	3/4-16	7/8-14	1 1/8	1	3/8	3/4	15/16	2 7/8	3.90	1 3/8	3/8-24	5 5/8	3 3/4	5/8	1 11/32	1	7/32	7/16	2.76	1/2	-	3/8	
	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1 1/4			5 7/8												
<b>4</b>	1	1	3/4-16	7/8-14	1 1/8	1	3/8	3/4	15/16	3 1/4	4.70	1 3/8	3/8-24	5 5/8	4 1/2	5/8	1 3/8	1	1/8	7/16	3.32	1/2	-	3/8	
	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1 1/4			5 7/8												
<b>5</b>	1	1	3/4-16	7/8-14	1 1/8	1	3/8	3/4	15/16	3 3/4	5.80	1 13/16	1/2-20	5 7/8	5 1/2	5/8	1 3/8	1 1/4	5/8	4.10	1/2	-	1/2		
	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1 1/4			6 1/8												
<b>6</b>	1	1	3/4-16	1 1/4-12	1 1/2-12	2	1	7/8	1 1/4			6 3/8													
	2	1	3/4	1 1/4-12	1 1/2-12	2	1	7/8	1 1/8			6 7/8													
<b>8</b>	1	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	7/8	1	4 1/2	6.90	1 13/16	1/2-20	6 5/8	6 1/2	3/4	1 5/8	1 3/8	5/8	4.88	3/4	-	1/2
	2	1	3/4	1 1/4-12	1 1/2-12	2	1	7/8	1 1/8			7													
<b>10</b>	1	1	3/4	1 1/4-12	1 1/2-12	2	1	7/8	-	7/8	6 3/8	11.20	2 11/16	3/4-16	8 1/4	10 5/8	-	2	1 3/4	7/8	7.92	1	-	3/4	
	2	2	1 1/2	1 1/4-12	1 3/4-12	2	1/4	2	-				8 3/8												
<b>12</b>	3	2	1 1/2	1 7/8-12	2 1/4-12	3	2	1/4	2	-	7/8	6 3/4	13.30	2 11/16	3/4-16	8 5/8	12 3/4	-	2	1 5/8	7/8	9.40	1	-	3/4
	2	2	1/2	1 7/8-12	2 1/4-12	3	2	1/4	-				9 1/8												
	3	3	2 1/4-12	2 3/4-12	3	1/2	2	1/4	-				9 1/8												




Model LNM  
NFPA Style MX0







Model LNA  
NFPA Style MX1

**For models LNA and LNC up to 6" bore:**  
If the cylinder will be mounted directly onto the rod-end face and the standard NFPA "W" dimension is required, an optional spacer plate is available. For this option, choose letter "F" in the options section of the nomenclature page when creating the cylinder model number.





**model LNB, LNC**

BORE	ROD	MM	KK	CC	A	WF	W	V	B	AA	BB	DD	+ STR	ZJ	E	F	G	J	K	R	EE	NPTF	SAE	XX							
<b>1 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	5/8	3/4	1 11/16	2.02	1		1/4-28	4	5/8	2	3/8	1	3/16	15/16	5/16	1.43	3/8	-	1/4						
	2	1	3/4-16	7/8-14	1	1/8	1	3/8	1					5																	
<b>2</b>	2	1	5/8	7/16-20	1/2-20	3/4	1	5/8	3/4	2	7/32	2.60	1	1/8	5/16-24	4	5/8	2	1/2	3/8	1	3/16	15/16	3/8	1.84	3/8	-	5/16			
	3	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1	1/4			5																	
<b>2 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	5/8	13/16	2	5/16	3.10	1	1/8	5/16-24	4	3/4	3	3/8	1	1/4	1		3/8	2.19	3/8	-	5/16				
	2	1	3/4-16	7/8-14	1	1/8	1	3/8	1					5																	
<b>3 1/4</b>	3	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1	1/4			5																	
	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1	1/4			5																	
<b>3</b>	3	1	3/4	1 1/4-12	1 1/2-12	2	1	7/8	1	1/4				5																	
	1	1	3/4-16	7/8-14	1	1/8	1	3/8	3/4	15/16	3	1/4	4.70	1	3/8	3/8-24	5	5/8	4	1/2	5/8	1	3/8	1	1/8	7/16	3.32	1/2	-	3/8	
<b>4</b>	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1				5																	
	3	1	3/4	1 1/4-12	1 1/2-12	2	1	7/8	1	1/4				6																	
<b>5</b>	1	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1				6																	
	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	1				6																	
<b>6</b>	3	1	3/4	1 1/4-12	1 1/2-12	2	1	7/8	1	1/8				6																	
	2	1	3/4	1 1/4-12	1 1/2-12	2	1	7/8	1	1/8				6																	
<b>8</b>	3	2	1 1/2-12	1 3/4-12	2	1/4	2	1	1/4					7																	
	1	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	-		5/8	5	3/4	9.10	2	5/16	5/8-18	6	3/4	8	1/2	-	1	5/8	1	3/8	3/4	6.44	3/4	-
<b>10</b>	2	2	1 3/4	1 1/4-12	1 1/2-12	2	1	7/8	-					7																	
	3	2	1 1/2-12	1 3/4-12	2	1/4	2	-						7																	
<b>12</b>	1	2	1 1/2-12	1 3/4-12	2	1/4	2	-		7/8	6	3/4	13.30	2	11/16	3/4-16	8	7/8	10	5/8	-	2	1	3/4	7/8	7.92	1	-	3/4		
	2	2	1 1/2	1 7/8-12	2	1 1/4-12	3	2	1/4	-				8																	
<b>12</b>	3	3	2 1/4-12	2 3/4-12	3	1/2	2	1/4	-					8																	
														9	1/8																
														9	1/8																


**Model LNB**  
NFPA Style MX2

**Model LNC**  
NFPA Style MX3

For models LNA and LNC up to 6" bore:



If the cylinder will be mounted directly onto the rod-end face and the standard NFPA "W" dimension is required, an optional spacer plate is available. For this option, choose letter "F" in the options section of the nomenclature page when creating the cylinder model number.





*Detail of optional thicker mounting plate (F1).*

#### **Models LR and LRS with optional thicker mounting flange plate**


**Note:** For the LR and LRS models – if the protruding hub is to be used as a mounting spigot, use the table values for B and V to ensure proper fit. If B dia. is too large and existing equipment cannot be modified, a thicker mounting flange plate (F1) is available that will recess the hub. An equivalent rod extension will accompany the increase in plate thickness. For this option, choose letter "U" in the options section of the nomenclature page when creating the cylinder model number.




## Model LR NFPA Style MF1





**Model LRS**  
NFPA Style MF5




**model LB, LBS**




**Model LB**  
NFPA Style MF2





**Model LBS**  
**NFPA Style MF6**



## model LTR, LTB





ROD DIA.										+ STROKE		EE						NPTF		XX			
BORE	ROD	MM	KK	CC	A	WJ	WG	B	V	XG	XJ	ZG	E	G	J	TD	TL	UT					
<b>1 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	1 1/8	1 11/16	3/4	1 3/4	4 1/8	4 3/4	2	1 3/16	15/16	1	1	4	3/8	-	1/4		
	2	1	3/4-16	7/8-14	1 1/8	1 3/8	1 1/2			2 1/8	4 1/2	5 1/8											
<b>2</b>	2	1	3/4-16	7/8-14	1 1/8	1 3/8	1 1/2			2 1/8	4 1/2	5 1/8	2 1/2	1 3/16	15/16	1	1	4 1/2	3/8	-	5/16		
	3	1	3/8	1-14	1 1/4-12	1 5/8	1 5/8	1 3/4		2 3/8	4 3/4	5 3/8											
<b>2 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	1 1/8	2 5/16	13/16	1 3/4	4 1/4	4 7/8	3	1 1/4	1	1	1	5	3/8	-	5/16		
	2	1	3/4-16	7/8-14	1 1/8	1 3/8	1 1/2			2 1/8	4 5/8	5 1/4											
<b>3 1/4</b>	1	1	3/4-16	7/8-14	1 1/8	1 3/8	1 1/2	2 7/8	15/16	2 1/4	5	5 3/4	3	3/4	1 11/32	1	7/32	1	1	5 3/4	1/2	-	3/8
	2	1	3/8	1-14	1 1/4-12	1 5/8	1 5/8	1 3/4		2 1/2	5 1/4	6											
<b>4</b>	3	1	3/4	1 1/4-12	1 1/2-12	2	1 7/8	2		2 3/4	5 1/2	6 1/4	5	1 1/2	1 3/8	1 1/8	1	1	6 1/2	1/2	-	3/8	
	1	1	3/4-16	7/8-14	1 1/8	1 3/8	1 7/16	3 1/4	15/16	2 1/4													
<b>5</b>	2	1	3/8	1-14	1 1/4-12	1 5/8	1 5/8	1 11/16		2 1/2	5 1/2	6 3/16	5	1/2	1 3/8	1 1/4	1	1	7 1/2	1/2	-	1/2	
	3	1	3/4	1 1/4-12	1 1/2-12	2	1 7/8	1 15/16		2 3/4	5 3/4	6 7/16											
<b>6</b>	1	1	3/8	1-14	1 1/4-12	1 5/8	1 9/16	1 3/4	4 1/2	1	2 5/8	5 7/8	6 3/4	6	1/2	1 5/8	1 3/8	1 3/8	9 1/4	3/4	-	1/2	
	2	1	3/4	1 1/4-12	1 1/2-12	2	1 11/16	2		2 7/8	6 1/8	7											
<b>8</b>	3	2	1 1/2-12	1 3/4-12	2	1 1/4	1 15/16	2 1/8		3	6 1/4	7 1/8	8	1/2	1 5/8	1 9/16	1 3/8	1 3/8	11 1/4	3/4	-	5/8	
	2	1	3/4	1 1/4-12	1 1/2-12	2	1 3/4	2 1/16		2 7/8	6 1/4	7 3/16											
<b>10</b>	3	2	1 1/2	1 7/8-12	2 1/4-12	3	2 1/16	2 3/8		3 3/8	7 5/8	8 3/4	10	5/8	2	1 15/16	1 3/4	1 3/4	14 1/8	1	-	3/4	
	1	2	1 1/2-12	1 3/4-12	2	1/4	1 11/16	2 1/8	6 3/4	7/8	3 1/8	7 7/8	9										
<b>12</b>	2	2	1 1/2	1 7/8-12	2 1/4-12	3	1 15/16	2 3/8		3 3/8	8 1/8	9 1/4	12	3/4	2	1 15/16	1 3/4	1 3/4	16 1/4	1	-	3/4	
	3	3	2 1/4-12	2 3/4-12	3	1/2	1 15/16	2 3/8		3 3/8	8 1/8	9 1/4											




Model LTR

NFPA Style MT1





Model LTB

NFPA Style MT2





## model LD, LT

ROD DIA.		BORE	ROD	MM	KK	CC	A	WF	B	V	XI (min)	BD	+ STR	+2xSTR	EE			NPTF	SAE	TD	TL	TM	TY	UM	XX				
1 1/2	2												LD	ZM	E	G	J												
1	1	5/8	1	7/16-20	1/2-20	3/4	1	1	1 11/16	3/4	2 7/8	1 1/4	3	7/8	6 1/8	2	1 3/16	15/16	3/8	-	1	1	2 1/2	2 1/4	4 1/2	1/4			
2	1	3/4	1	3/4-16	7/8-14	1	1/8	1	3/8		3 1/4		3	7/8	6 7/8						1	1	3	2 3/4	5	5/16			
2	2	1	3/4	3/4-16	7/8-14	1	1/8	1	3/8		3 3/8		3	7/8	6 7/8						1	1	3	1/2	3 1/4	5 1/2	5/16		
2 1/2	2	1	3/4	3/4-16	7/8-14	1	1/8	1	3/8		3 7/16		3	1 3/8	7 3/8						1	1	3	1/2	3 1/4	5 1/2	5/16		
2 1/2	3	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8		3 5/8		3	1 3/8	7 1/2						1	1	3	1/2	3 1/4	5 1/2	5/16		
3 1/4	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8		3 11/16		3	1 3/8	7 1/2	3 3/4	1 11/32	1 7/32	1/2	-	1	1	4	1/2	4 1/4	6 1/2	3/8		
3 1/4	3	1	3/4	1-14	1 1/4-12	1	5/8	1	5/8		3 29/32		3	1 3/4	8						1	1	3	1/2	3 1/4	5 1/2	5/16		
4	1	1	3/4	3/4-16	7/8-14	1	1/8	1	3/8	3 1/4	15/16	3 11/16	1 3/4	4	1/2	7 1/2	4 1/2	1 3/8	1 1/8	1/2	-	1	1	5	1/4	5	7 1/4	3/8	
4	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8		3 15/16		3	1 3/8	8						1	1	6	1/4	6	8 1/4	1/2		
4	3	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8		4 3/16		3	1 3/8	8 1/2						1	1	6	1/4	6	8 1/4	1/2		
5	1	1	3/8	3/4-16	7/8-14	1	1/8	1	3/8	3 3/4	15/16	3 13/16	2	4	5/8	7 3/4	5 1/2	1 3/8	1 1/4	1/2	-	1	1	6	1/4	6	8 1/4	1/2	
5	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8		4 1/16		3	1 3/8	8 3/4						1	1	6	1/4	6	8 1/4	1/2		
6	1	1	3/8	1 1/4-12	1 1/2-12	2		1	7/8		4 5/16		3	1 3/8	8 3/4						1	3/8	1 3/8	7 5/8	7 3/8	10 3/8	1/2		
6	2	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8		4 11/16		3	2	9 1/4						1	3/8	1 3/8	7 5/8	7 3/8	10 3/8	1/2		
6	3	2	1	1 1/2-12	1 3/4-12	2	1/4	2		4 13/16		3	2	9 1/2						1	3/8	1 3/8	9 3/4	9 1/2	12 1/2	5/8			
8	1	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	5 3/4	5/8	4 9/16	2 1/2	5	3/8	8 7/8	8 1/2	1 5/8	1 3/8	3/4	-	1	3/8	1 3/8	9 3/4	9 1/2	12 1/2	5/8	
8	2	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8		4 13/16		3	2	9 3/8						1	3/8	1 3/8	9 3/4	9 1/2	12 1/2	5/8		
8	3	2	1	1 1/2-12	1 3/4-12	2	1/4	2		4 15/16		3	2	9 5/8						1	3/8	1 3/8	12	11 3/4	15 1/2	3/4			
10	1	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8	6 3/8	7/8	5 7/16	3	6	5/8	10 3/8	10 5/8	2	1 3/4	1	-	1	3/4	1 3/4	12	11 3/4	15 1/2	3/4	
10	2	2	1	1 1/2-12	1 3/4-12	2	1/4	2			5 9/16		3	2	10 5/8						1	3/8	1 3/8	14	13 3/4	17 1/2	3/4		
10	3	2 1/2	1	1 7/8-12	2 1/4-12	3		2	1 1/4		5 13/16		3	2	11 1/8						1	-	1	3/4	1 3/4	12	11 3/4	15 1/2	3/4
12	2	2 1/2	1	1 7/8-12	2 1/4-12	3		2	1 1/4		5 13/16		3	3	11 5/8						1	-	1	3/4	1 3/4	14	13 3/4	17 1/2	3/4
12	3	3	2	2 1/4-12	2 3/4-12	3	1/2	2	1 1/4		5 13/16		3	3	11 5/8						1	-	1	3/4	1 3/4	14	13 3/4	17 1/2	3/4




Model LD




Model LT


Warning: Trunnion mounted cylinders swivel in one direction and are designed to carry shear loads only. Pins must be held rigidly and in accurate alignment. Improper mounting may result in failure of mount.



BORE	ROD DIA.	MM	KK	CC	A	WF	V	B	ADD STROKE		ADD STR 1&2		EE				NPTF SAE			MR NF XX				
									ZJ	LB	XXC	CD	G	J	L	3/8	-	1/2	1	5/8	1/4			
<b>1 1/2</b>	1	5/8	7/16-20	1/2-20	3/4	1	3/4	1 11/16	4 5/8	3 5/8	10 3/8	1/2	1	3/16	15/16	3/4	3/8	-	1/2	1	5/8	1/4		
	2	1	3/4-16	7/8-14	1	1/8	1	3/8	5								3/8	-	1/2	1	3/4	5/16		
	2	1	5/8	7/16-20	1/2-20	3/4	1	3/4	2 7/32	4 5/8	3 5/8	10 1/2	1/2	1	3/16	15/16	3/4	3/8	-	1/2	1	3/4	5/16	
<b>2 1/2</b>	2	1	3/4-16	7/8-14	1	1/8	1	3/8	5															
	3	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	5 1/4														
	1	5/8	7/16-20	1/2-20	3/4	1	13/16	2 5/16	4 3/4	3 3/4	10 3/4	1/2	1	1/4	1	3/4	3/8	-	1/2	1	3/4	5/16		
<b>3 1/4</b>	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	5 1/4														
	3	1	3/4	1-14	1 1/4-12	1	5/8	1	5/8	5 3/8														
	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	5 7/8														
<b>4</b>	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	5 7/8														
	3	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8	6 1/8														
	1	1	3/4-16	7/8-14	1	1/8	1	3/8	15/16	3 1/4	5 1/4	13 1/2	3/4	1	11/32	1	7/32	1	1/4	1/2	3/4	2 1/2	3/8	
<b>5</b>	2	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	6 1/8														
	3	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8	6 3/8														
	1	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	6 5/8														
<b>6</b>	2	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8	6 7/8														
	3	2		1 1/2-12	1 3/4-12	2	1/4	2		7														
	1	1	3/8	1-14	1 1/4-12	1	5/8	1	5/8	6 1/8														
<b>8</b>	2	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8	7														
	3	2		1 1/2-12	1 3/4-12	2	1/4	2		7 1/8														
	1	1	3/4	1 1/4-12	1 1/2-12	2		1	7/8	7/8	6 3/8	8 1/4	6 3/8	20 11/16	1	3/8	2	1	3/4	2 1/8	1	-	1 3/8	3 11/16
<b>10</b>	2	2		1 1/2-12	1 3/4-12	2	1/4	2		8 3/8														
	3	2	1/2	1 7/8-12	2 1/4-12	3		2	1/4	8 5/8														
	1	2		1 1/2-12	1 3/4-12	2	1/4	2		7/8	6 3/4	8 7/8	6 7/8	21 15/16	1	3/4	2	1	5/8	2 1/4	1	-	1 3/4	3 11/16
<b>12</b>	2	2	1/2	1 7/8-12	2 1/4-12	3		2	1/4	9 1/8														
	3	3		2 1/4-12	2 3/4-12	3	1/2	2	1/4	9 1/8														



Model LCH




Model LCR







## model LCHR

BORE	ROD	MM	KK	CC	A	WF	V	B	ADD STROKE		ADD STR 1,2&3		CD	G	J	L	EE		NPTF	SAE	MR	NF	XX			
									ZJ	LB	XZJ															
1 1/2	1	5/8	7/16-20	1/2-20	3/4	1	3/4	1 11/16	4	5/8 3 5/8	14	1/4	1/2	1	3/16	15/16	3/4	3/8	-	1/2	1	5/8	1/4			
	2	1	3/4-16	7/8-14	1	1/8	1	3/8	5		14	5/8														
	1	5/8	7/16-20	1/2-20	3/4	1	3/4	2 7/32	4	5/8 3 5/8	14	3/8	1/2	1	3/16	15/16	3/4	3/8	-	1/2	1	3/4	5/16			
2	2	1	3/4-16	7/8-14	1	1/8	1	3/8	5		14	3/4														
	3	1	3/8	1-14	1 1/4-12	1	5/8	1 5/8	5	1/4	15															
	1	5/8	7/16-20	1/2-20	3/4	1	13/16	2 5/16	4	3/4 3 3/4	14	3/4	1/2	1	1/4	1	3/4	3/4	3/8	-	1/2	1	3/4	5/16		
2 1/2	2	1	3/4-16	7/8-14	1	1/8	1	3/8	5	1/8	15	1/8														
	3	1	3/8	1-14	1 1/4-12	1	5/8	1 5/8	5	3/8	15	3/8														
	1	1	3/4-16	7/8-14	1	1/8	1	3/8	5	5/8 4 1/4	17	7/8	3/4	1	11/32	1	7/32	1	1/4	1/2	-	3/4	2	1/2	3/8	
3 1/4	2	1	3/8	1-14	1 1/4-12	1	5/8	1 5/8	5	7/8	18	1/8														
	3	1	3/4	1 1/4-12	1 1/2-12	2		1 7/8	6	1/8	18	3/8														
	1	1	3/4-16	7/8-14	1	1/8	1	3/8	5	5/8 4 1/4	17	7/8	3/4	1	3/8	1	1/8	1	1/4	1/2	-	3/4	2	1/2	3/8	
4	2	1	3/8	1-14	1 1/4-12	1	5/8	1 5/8	5	7/8	18	1/8														
	3	1	3/4	1 1/4-12	1 1/2-12	2		1 7/8	6	1/8	18	3/8														
	1	1	3/4-16	7/8-14	1	1/8	1	3/8	5	5/8 4 1/2	18	7/8	3/4	1	3/8	1	1/4	1	1/4	1/2	-	3/4	2	3/4	1/2	
5	2	1	3/8	1-14	1 1/4-12	1	5/8	1 5/8	6	1/8	19	1/8														
	3	1	3/4	1 1/4-12	1 1/2-12	2		1 7/8	6	3/8	19	3/8														
	1	1	3/8	1-14	1 1/4-12	1	5/8	1 5/8	1	4 1/2	6	5/8 5	21	1/8	1	1	5/8	1	3/8	1	1/2	3/4	-	1	3	1/2
6	2	1	3/4	1 1/4-12	1 1/2-12	2		1 7/8	6	7/8	21	3/8														
	3	2	1 1/2-12	1 3/4-12	2	1/4	2		7		21	1/2														
	1	1	3/8	1-14	1 1/4-12	1	5/8	1 5/8	6	3/4 5 1/8	22	3/16	1	1	5/8	1	3/8	1	1/2	3/4	-	1	3	11/16	5/8	
8	2	1	3/4	1 1/4-12	1 1/2-12	2		1 7/8	7		22	7/16														
	3	2	1 1/2-12	1 3/4-12	2	1/4	2		7	1/8	22	9/16														
	1	1	3/4	1 1/4-12	1 1/2-12	2		1 7/8	8	1/4 6 3/8	26	13/16	1	3/8	2		1	3/4	2	1 1/8	1	-	1	3/8	3 11/16	3/4
10	2	2	1	3/4-12	1 3/4-12	2	1/4	2	8	3/8	26	15/16														
	3	2	1/2	1 7/8-12	2 1/4-12	3		2 1/4	8	5/8	27	3/16														
	1	2	1 1/2-12	1 3/4-12	2	1/4	2		8	7/8 6 7/8	28	9/16	1	3/4	2		1	5/8	2	1 1/4	1	-	1	3/4	3 11/16	3/4
12	2	2	1/2	1 7/8-12	2 1/4-12	3		2 1/4	9	1/8	28	13/16														
	3	3	2 1/4-12	2 3/4-12	3	1/2	2 1/4		9	1/8	28	13/16														



Model LCHR

**Rod End Styles**Standard Male Thread  
NFPA Style SMOversize Male Thread  
NFPA Style IMFemale Thread  
NFPA Style SFFull Thread  
NFPA Style FM**Accessories for Rod End**

BORE	ROD DIA. MM	THREAD SIZE	ROD CLEVIS	LUG		ROD EYE	CLEVIS	SELF ALIGNING		
				MOUNTING BRACKET	PIVOT PIN			MOUNTING BRACKET	ROD EYE	MOUNTING BRACKET
1 1/2	2	5/8	7/16-20	HC15	P3	HE15	HCM15	HWE15	HWM15	HWP15
		5/8	1/2-20	HC15C	P3	HE15C	HCM15	N/A	N/A	N/A
		1	3/4-16	HC2	P4	HE2	HCM2	HWE2	HWM2	HWP2
	4	1	7/8-14	HC2C	P6	HE2C	HCM32	N/A	N/A	N/A
		1 3/8	1-14	HC32	P6	HE32	HCM32	HWE32	HWM32	HWP32
		1 3/8	1 1/4-12	HC4	HP4	HE4	HCM4	HWE4	HWM4	HWP4
6	5	1 3/4	1 1/4-12	HC4	HP4	HE4	HCM4	HWE4	HWM4	HWP4
		1 3/4	1 1/2-12	HC5	HM5	HE5	HCM5	HWE5	HWM5	HWP5
	8	2	1 1/2-12	HC5	HM5	P12	HCM5	HWE5	HWM5	HWP5
		2	1 3/4-12	HC5C	HM6	HP6	HE5C	HCM6	N/A	N/A


**Accessories for Blind End**

BORE	MOUNTING BRACKET model LC	MOUNTING BRACKET model LE	PIVOT PIN	SELF ALIGNING	
				MOUNTING BRACKET	PIVOT PIN
1 1/2	2	2 1/2	HM15	HCM15	P3
3 1/4	4	5	HM25	HCM2	P4
	6	8	HM32	HCM32	P6
		10	HM4	HCM4	HP4
		12	HM5	HCM5	P12
				HWM5	HWP5

**Rod Eye**

Adapts to HCM clevis-type mounting bracket


PART	HE15	HE15C	HE2	HE2C	HE32	HE4	HE5	HE5C	HE6	HE7	HE7C	HE8
A	3/4	3/4	1 1/8	1 1/8	1 5/8	2	2 1/4	2 1/4	3	3 1/2	3 5/8	3 1/2
CA	1/2	1/2	2 1/16	2 3/8	2 13/16	3 7/16	4	4 3/8	5	5 13/16	6 1/2	6 1/8
CB	3/4	3/4	1 1/4	1 1/2	1 1/2	2	2 1/2	2 1/2	2 1/2	3	3 1/2	3
CD	1/2	1/2	3/4	1	1	1 3/8	1 3/4	2	2	2 1/2	3	3
ER	5/8	5/8	7/8	1 1/8	1 3/16	1 9/16	2	2 7/8	2 1/2	2 13/16	3 1/4	3 1/4
KK	7/16-20	1/2-20	3/4-16	7/8-14	1-14	1 1/4-12	1 1/2-12	1 3/4-12	1 7/8-12	2 1/4-12	2 3/4-12	2 1/2-12



**Detachable Clevis - MP-1 Mount (NFPA)**


Mounts on cylinder and adapts to HM eye-type mounting bracket

PART	LMP1-15	LMP1-2	LMP1-25	LMP1-32	LMP1-4	LMP1-5	LMP1-6
CB	0.76	0.76	0.76	1.26	1.26	1.26	1.51
CD	1/2	1/2	1/2	3/4	3/4	3/4	
CW	1/2	1/2	1/2	5/8	5/8	5/8	3/4
DD	1/4-28	5/16-24	5/16-24	3/8-24	3/8-24	1/2-20	1/2-20
E	2	2 1/2	3	3 3/4	4 1/2	5 1/2	6 1/2
F	3/8	3/8	3/8	5/8	5/8	5/8	3/4
J	5/8	5/8	5/8	7/8	7/8	7/8	1 1/8
SFL	3/4	3/4	3/4	1 1/4	1 1/4	1 1/4	1 1/2
MR	5/8	5/8	5/8	7/8	7/8	7/8	1 1/8
R	1.43	1.84	2.19	2.76	3.32	4.10	4.88

**Detachable Clevis - MP-2 Mount (NFPA)**


Mounts on cylinder and adapts to HM eye-type mounting bracket

PART	LMP2-15	LMP2-2	LMP2-25	LMP2-32	LMP2-4	LMP2-5	LMP2-6
CB	0.76	0.76	0.76	1.26	1.26	1.26	1.51
CD	1/2	1/2	1/2	3/4	3/4	3/4	1
CW	1/2	1/2	1/2	5/8	5/8	5/8	3/4
DD	1/4-28	5/16-24	5/16-24	3/8-24	3/8-24	1/2-20	1/2-20
E	2	2 1/2	3	3 3/4	4 1/2	5 1/2	6 1/2
F	3/8	3/8	3/8	5/8	5/8	5/8	3/4
L	3/4	3/4	3/4	1 1/4	1 1/4	1 1/4	1 1/2
MR	5/8	5/8	5/8	7/8	7/8	7/8	1 1/8
R	1.43	1.84	2.19	2.76	3.32	4.10	4.88

**Eye Type Mounting Bracket**


Adapts to LC mount cylinder or HC rod clevis

PART	HM15	HM25	HM32	HM4	HM5	HM6
CB	3/4	1 1/4	1 1/2	2	2 1/2	2 1/2
CD	1/2	3/4	1	1 3/8	1 3/4	2
DD	13/32	17/32	21/32	21/32	29/32	1 1/16
E	2 1/2	3 1/2	4 1/2	5	6 1/2	7 1/2
F	3/8	5/8	3/4	7/8	7/8	1
FL	1 1/8	1 7/8	2 1/4	3	3 1/8	3 1/2
MR	1/2	3/4	1	1 3/8	1 3/4	2
R	1.63	2.56	3.25	3.81	4.95	5.75

**Rod Clevis**

Adapts to male thread on piston rod


PART	HC15	HC15C	HC2	HC2C	HC32	HC4	HC5	HC5C
A	3/4	3/4	1 1/8	1 5/8	1 5/8	2	2 1/4	3
CB	0.765	0.765	1.265	1.515	1.515	2.032	2.531	2.531
CD	1/2	1/2	3/4	1	1	1 3/8	1 3/4	2
CE	1 1/2	1 1/2	2 3/8	3 1/8	3 1/8	4 1/8	4 1/2	5 1/2
CW	1/2	1/2	5/8	3/4	3/4	1	1 1/4	1 1/4
CR	1/2	1/2	3/4	1	1	1 3/8	1 3/4	2
KK	7/16-20	1/2-20	3/4-16	7/8-14	1-14	1 1/4-12	1 1/2-12	1 3/4-12

**Pivot Pin**

Comes complete with cotter pins

Adapts to HC rod clevis or HCM clevis-type mounting bracket


PART	P3	P4	P6	HP4	P12	HP6
CD	1/2	3/4	1	1 3/8	1 3/4	2
CL	1 3/4	2 1/2	3	4	4 7/8	5 1/8
CP	2 5/16	3 1/8	3 3/4	4 13/16	6 1/8	6



**Clevis Type Mounting Bracket**

Adapts to LE mount cylinder or HE rod eye

PART	HCM15	HCM2	HCM32	HCM4	HCM5	HCM6
CB	25/32	1 9/32	1 17/32	2 1/32	2 9/16	2 9/16
CD	1/2	3/4	1	1 3/8	1 3/4	2
CW	1/2	5/8	3/4	1	1 1/4	1 1/4
DD	13/32	17/32	21/32	21/32	15/16	1 1/16
E	3 1/2	5	6 1/2	7 1/2	9 1/2	12 3/4
F	1/2	5/8	3/4	7/8	7/8	1
FL	1 1/2	1 7/8	2 1/4	3	3 5/8	4 1/4
MR	1/2	3/4	1	1 3/8	1 3/4	2
R	2.55	3.82	4.95	5.73	7.50	9.40

**Pivot Pin for Self-Aligning Rod Eye**

Comes complete with cotter pins


Adapts to HWM mounting bracket

PART	HWP15	HWP2	HWP32	HWP4	HWP5
CD	1/2	3/4	1	1 3/8	1 3/4
CL	1 5/16	2	2 17/32	3 3/32	3 7/16
CP	1 7/8	2 9/16	3 3/16	3 3/4	4 3/16

**Self-Aligning Rod Eye - Female**


Adapts to male thread on piston rod

PART	HWE15	HWE2	HWE32	HWE4	HWE5
A	3/4	1 1/8	1 5/8	2	2 1/4
CD	1/2	3/4	1	1 3/8	1 3/4
CK	7/16	21/32	7/8	1 3/16	1 17/32
JW	3/4	1 3/8	1 1/2	2	2 1/2
KK	7/16-20	3/4-16	1-14	1 1/4-12	1 1/2-12
LW	1 3/4	2 3/4	3 5/8	4 1/2	5 5/8
RW	7/8	1 1/4	1 1/2	2	2 3/4
LK	5/8	1 1/4	1 5/8	2 1/8	2 5/8

**Self-Aligning Rod Eye - Male**


Adapts to female thread on piston rod

PART	HRES-1	HRES-2	HRES-3	HRES-4	HRES-5	HRES-6
A	11/16	1	1 1/2	2	2 1/8	2 7/8
CD	1/2	3/4	1	1 3/8	1 3/4	2
CE	7/8	1 1/4	1 7/8	2 1/8	2 1/2	2 3/4
CK	7/16	21/32	7/8	1 3/16	1 17/32	1 3/4
JL	7/8	1 5/16	1 1/2	2	2 1/4	2 3/4
KK	7/16-20	3/4-16	1-14	1 1/4-12	1 1/2-12	1 7/8-12
LE	3/4	1 1/16	1 7/16	1 7/8	2 1/8	2 1/2
RW	7/8	1 1/4	1 3/8	1 13/16	2 3/16	2 5/8

**Mounting Bracket for Self-Aligning Rod Eye**

Adapts to LW mount cylinder, HWE and HRES rod eye

PART	HWM15	HWM2	HWM32	HWM4	HWM5	HWM6
CD	1/2	3/4	1	1 3/8	1 3/4	2
CK	7/16	21/32	7/8	1 3/16	1 17/32	1 3/4
CW	5/16	1/2	5/8	3/4	3/4	7/8
DD	13/32	17/32	21/32	21/32	15/16	1 1/16
E	2 1/2	3 1/2	4 1/2	5	6 1/2	7 1/2
F	3/8	9/16	11/16	13/16	15/16	15/16
FL	1 1/2	2 1/16	2 7/16	3 1/16	3 15/16	4 3/16
MR	1/2	3/4	1	1 3/8	1 3/4	2
R	1.63	2.55	3.25	3.82	4.95	5.73



## L-SERIES PARTS LIST

No.	DESCRIPTION	ROD SIZE >	1 1/2	2	5/8	1	1 3/8	5/8	1	2 1/2	3 1/4	1	1 3/8	1 3/4	4	5	6
1	PISTON	QTY	1	11.15		1.20		1.25		1.32		1.40		1.48	1	1 3/8	1 3/4
3	CUSHION SLEEVE		1	N/A	N/A	31.25		31.25		31.32		31.40		31.48	1	1 3/8	1 3/4
4	ROD - MALE		1	4L1506-4L1510-	4L1506-4L1510-	4L2010-4L2013-		4L2010-4L2013-		4L2010-4L2013-		4L2010-4L2013-		4L2010-4L2013-		4L2010-4L2013-	
26	ROD - FEMALE		1	26L1506-26L1510-	26L1506-26L1510-	26L2010-26L2013-		26L2010-26L2013-		26L3210-26L3213-		26L4010-26L4013-		26L4010-26L4013-		26L5010-26L5013-	
44	ROD - COMMON		1	44L1506-44L1510-	44L1506-44L1510-	44L2010-44L2013-		44L2010-44L2013-		44L3210-44L3213-		44L4010-44L4013-		44L4010-44L4013-		44L5010-44L5013-	
5	BARREL (NITROTEC STEEL)		1	5LN15-	5LN20-	5LSB25-		5LSB25-		5LSB32-		5LSB40-		5LSB50-		5LN60-	
5	BARREL (CHROMED STEEL)		1	5LSB15-		5LA120-		5LA120-		5LA32-		5LA40-		5LA50-		5LSB60-	
5	BARREL (ALUMINUM)		1	5LA15-		5LA15-		5LA15-		5LA32-		5LA40-		5LA50-		5LA60-	
6	GLAND BUSHING		1	6L1562-6L1510	6L1562	6L2010		6L2010		6L2013		6L3210		6L3213		6L6013	
** 7	NEEDLE VALVE		2	*71.344	*71.344	*71.344		*71.344		71.344		71.344		71.344		71.344	
8	TIE ROD		4	8LT1A54-8LT1B154	8LT1A54-8LT1B154	8LT1A205-8LT1B205		8LT1A205-8LT1B205		8LT1A256-8LT1B256		8LT1A326-8LT1B326		8LT1A406-8LT1B406		8LT1A506-8LT1B506	
9	TIE-ROD, MODEL LT ONLY ***		4	8LT1A54-8LT1B154	8LT1A54-8LT1B154	8LT1A205-8LT1B205		8LT1A205-8LT1B205		8LT1A256-8LT1B256		8LT1A326-8LT1B326		8LT1A406-8LT1B406		8LT1A506-8LT1B506	
9	CUSHION SLEEVE SEAL		1	9A111	9A111			N/A		N/A		N/A		N/A		N/A	
** 9	PISTON SEAL		1	N/A	N/A	N/A		N/A		N/A		N/A		N/A		N/A	
** 10	PISTON SEAL		1	10A755-15	10A755-15	10A755-2		10A755-2		10A755-325		10A755-54		10A755-54		10A755-6	
** 11	CHECK SEAL-GLAND END(G or CBE)		1	11J110	11J110	11J110		11J110		11J110		11J110		11J110		11J110	
** 11A	CHECK SEAL-GLAND END(G or CBE)		1	11J110	11J110	11J110		11J110		11J110		11J110		11J110		11J110	
** 12	GLAND BUSHING SEAL		1	9A123	9A123	9A223		9A223		9A227		9A227		9A227		9A230	
** 13	ROD SEAL		1	13A06H	13A06H	13A06H		13A06H		13A13H		13A13H		13A13H		13A13H	
** 14	ROD WIPER		1	14H62	14H62	14H62		14H62		14H10		14H10		14H10		14H10	
15	GLAND BUSHING RETAINER		1	15A157	15A157	15A157		15A157		15A187		15A237		15A237		15A237	
** 16	NEEDLE VALVE SEAL		2	*9A009	*9A009	*9A009		*9A009		*9A009		*9A009		*9A009		*9A113	
17	LOCK NUT - TIE ROD (BLIND END)		4	19A004	19A004	19A005		19A005		19A005		19A005		19A005		19A008	
17A	LOCK NUT - TIE ROD (GLAND END)		4	19D004	19D004	19D005		19D005		19D005		19D005		19D005		19A008	
19	PISTON LOCKNUT (or NUTSPEAR)		1	***19.007	***19.007	***19.007		***19.007		19.0102		19.0102		19.0102		19.0102	
20	JAM NUT (OPTIONAL)		1	20R007	20R012	20R016		20R007		20R012		20R016		20R020		20R020	
** 21	BARREL SEAL		2	9A125	9A125	9A224		9A228		9A224		9A240		9A248		9A256	
22	HEAD BLIND END		1	L_15BC	L_15BC	L_15BC		L_15BC		L_25BC		L_48C		L_58C		L_68C	
23	HEAD GLAND END		1	L_15G	L_15G	L_15G		L_15G		L_25GC		L_48C		L_58C		L_68C	
24	TRUNNION-INTERMEDIATE		1	L115	L115	L120		L120		L125		L140		L140		L160	
** 33	CHECK BALL		1	N/A	N/A	N/A		N/A		N/A		N/A		N/A		N/A	
** 35	CHECK PLUG		1	N/A	N/A	N/A		N/A		N/A		N/A		N/A		N/A	
36	FRONT PLATE-RECTANGULAR		1	FP15R	FP20R	FP20R		FP20R		FP23R		FP40R		FP40R		FP60S	
38	FRONT PLATE-SQUARE		1	FP15S	FP20S	FP20S		FP20S		FP22S		FP40S		FP40S		FP60S	
38	FRONT PLATE-THICK (RECT.)		1	FP15GU	FP20RU	FP20RU		FP20RU		FP25RU		FP40SU		FP40SU		FP60SU	
38	FRONT PLATE-THICK (SQUARE)		1	FP15SU	FP20SU	FP20SU		FP20SU		FP25SU		FP40UF		FP40UF		FP60UF	
38	SPACER PLATE (modl option "F")		1	FP15F	FP20F	FP20F		FP20F		FP25F		BP15R		BP15R		BP60R	
38	BACK PLATE-RECTANGULAR		1	BP15R	BP20R	BP20R		BP20R		BP25R		BP40S		BP40S		BP60S	
38	BACK PLATE-SQUARE		1	BP15S	BP20S	BP20S		BP20S		BP25S		BP40S		BP40S		BP60S	
** 40	PISTON WEAR RING		1	40H1525	40H1525	40H1525		40H1525		40H15237		40H1537		40H1537		40H1537	
42	DETACHABLE CLEVIS - MP1		1	LMP2-15	LMP2-15	LMP2-22		LMP2-22		LMP2-32		LMP2-4		LMP2-4		LMP2-6	
43	DETACHABLE CLEVIS - MP2		1	LMP2-15	LMP2-15	LMP2-22		LMP2-22		LMP2-32		LMP2-4		LMP2-4		LMP2-6	
43	DETACHABLE CLEVIS - MP3		1	KL1562A	KL1510A	KL2032A		KL2032A		KL2510A		KL3210A		KL3210A		KL5017A	
43	SEAL KIT (PNEUMATIC)		1	KL1562A	KL1510A	KL2032A		KL2032A		KL2510A		KL3210A		KL3210A		KL6017A	

## SEE PAGE BEHIND PARTS DRAWING FOR "B" BORE THROUGH "12" BORE PARTS

## NOTES:

Cushioning is supplied as standard on all cylinders unless ordered otherwise. Apart no. having an underscore indicates a model letter code is required. See tables below.

Parts for a non-cushioned cylinder are the same as for cushioned except the check seals are not installed. For the 2 1/2" bore, 1 3/8" rod cylinder on the blind end, remove the check seal, on the gland end remove the cushion sleeve and cushion sleeve seal.

Part numbers terminating in a dash must have the stroke value added immediately afterward.

\* Contact the factory for cushioning options on the gland end of the 1 1/2" bore (both rod sizes), and the 2" bore (1" and 1 3/8" only rod sizes). For these cylinders, the quantity of needle valves and needle valve seals must be halved.

\*\* These parts are in the seal kit.

\*\*\* Tie-rod part numbers for model LT only have a stroke value suffix followed by a dash and then the required "X" value (see explanation following).

\*\*\*\* If cylinder is specified as non cushioned then supply 19.007 for piston lock nut.

\*\*\*\*\* If cylinder is specified as cushioned then supply 19.007 for piston lock nut.

## HEAD PARTS ARE MADE AS FOLLOWS:

1) SERIES - "L"

2) Use table (to right) to select head mounting style.

3) BORE 3-1/4" bore use 32, 4" bore use 4.

4) LOCATION: "B"=Blind G-Gland or Rod end.

5) CUSHIONED = "C"

(All heads are manufactured as cushioned.)

eg. Cyl. Model "LR5", 3-1/4" Bore, Cushioned

Gland end head "L322C"

Blind end head "LR322C"

eg. 4" bore, model LT, 12" stroke; "L4L0406-12"

eg. 4 1/2" bore, model LT, 1 3/8" rod (R3), 8" stroke, "L4L4010CC-8"

Note: if there is a P1st Rod Extension, the XI value in the Tie-Rod Part Number is reduced depending on trunnion position.

Note: if there is a P1st Rod Extension, the XI value in the Tie-Rod Part Number is reduced depending on trunnion position.

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

ROD PART NUMBER STRUCTURE:	LETTER CODE
1) COMPONENT No - "4"	1) COMPONENT No - "8"
2) SERIES - "L"	2) SERIES - "L"
3) CYL. MODEL - For LT model use table (to right) to select letter code	3) CYL. MODEL - For LT model use table (to right) to select letter code
4) ROD SIZE: 2 digits long as follows: eg. 1-3/4" rod = 17,	Note: some cyl. models use a common code.
5) OPTIONS: "CC" = CC thread, "F" = Full thread, "F" = Female thread, "U" = Rod End Trunnion for thicker Mg. Flange Plate(L and R LRS only), "T" = Rod End Trunnion, "B" = Blind End Trunnion, "D" = Male Rod of Double-Rod cylinder, "S" = Side-rapped Mount.	4) ROD SIZE - For LT MODEL ONLY: "A", "B" or "C"
"D" = 5/16", "12 - 3/4"	5) CYLINDER BORE (2 digits) ie. 20 = 2" bore
"S" = Side-rapped Mount.	6) TIE-ROD DIA. in 1/16ths of an inch ie. 5/16", 12 - 3/4"
eg. "T" stroke... "-"	7) STROKE VALUE, (to be preceded by a dash)
eg. "X" stroke... "-"	8) X DIMENSION, preceded by a dash. For Models LT Only

CYLINDER MODELS	LETTER CODE
LNA	A
LNB,LNC	B
LC,LE,LW	C
LD	D
LF,LTR,LTB,LNM	F
LCH	H
LMP,LB,LBS	P
LR,LRS	R
LT	T

eg. 4" bore, model LT, 12" stroke; "L4L0406-12"

eg. 4 1/2" bore, model LT, 1 3/8" rod (R3), 8" stroke, "L4L4010CC-8"

Note: for LT models the two-piece tie-rods are sold as a unit (one half may be a cap screw, depending on trunnion position).

Note: if there is a P1st Rod Extension, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced


equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced


equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is reduced

equally. For the above example with a 1" Rod Ext'n, the XI value in the Tie-Rod Part Number is

# L-Series Parts Drawing





## L-SERIES PARTS LIST

No.	DESCRIPTION	BORE >		8		10		12		12	
		ROD SIZE >	QTY	1 3/8	1 3/4	2	1 3/4	2	1 1/2	2	2 1/2
1	PISTON		1	1L80		1L100			1L120		
3	CUSHION SLEEVE		1	3L80		3L100			3L120		
4	ROD - MALE		1	4L80/13-	4L80/17-	4L80/20-	4L100/17-	4L100/20-	4L120/25-	4L120/30-	
26	ROD - FEMALE		1	26L80/13-	26L80/17-	26L80/20-	26L100/17-	26L100/20-	26L120/25-	26L120/30-	
44	ROD - COMMON		1	44L80/13-	44L80/17-	44L80/20-	44L100/17-	44L100/20-	44L120/25-	44L120/30-	
5	BARREL (NITROTEC STEEL)		1	5LN80-		5LN100-			5LN120-		
5	BARREL (CHROMED STEEL)		1	5L8B80-		5LA100-			5LA120-		
5	BARREL (ALUMINUM)		1	5LAM80-		5LM100-			5LM120-		
6	GLAND BUSHING		1	6L80/13	6L80/17	6L80/20	6L100/17	6L100/20	6L120/25	6L120/30	
** 7	NEEDLE VALVE		2	7A912		7A916			7A916		
8	TIE ROD		4	8LTA80/10-	8LTB80/10-	8LTC80/10-	8LTIA100/12-	8LTB100/12-	8LTC100/12-	8LTA120/12-	8LTB120/12-
8	TIE-ROD, MODEL LT ONLY ***		4	8LTA80/10-	8LTB80/10-	8LTC80/10-	8LTIA100/12-	8LTB100/12-	8LTC100/12-	8LTA120/12-	8LTB120/12-
9	PISTON SEAL, INTERNAL		1	9A216		9A220			9A223		
** 10	PISTON SEAL		2	10A980H		10A9100H			10A9120H		
** 11	CHECK SEAL-GLAND END(CG or CBE)		1	11J170		11J1100			11J1100		
** 11A	CHECK SEAL-BLIND END(CB or CBE)		1	11J122		11J128			11J132		
** 12	GLAND BUSHING SEAL		1	9A236		9A242			9A245		
** 13	ROD SEAL		1	13A13H	13A17H	13J20H	13A17H	13J20H	13J25H	13J30H	
** 14	ROD WIPER		1	14H13	14H17	14H20	14H17	14H20	14H25	14H30	
** 16	NEEDLE VALVE SEAL		2	9A113		9A210			9A210		
17	LOCK NUT - TIE ROD		8	19A010		19A012			19A012		
19	PISTON LOCKNUT		1	19J016		19J020			19J024		
20	JAM NUT (OPTIONAL)		1	20R016	20R020	20R024	20R020	20R030	20R024	20R030	20R036
** 21	BARREL SEAL		2	9A265		9A273			9A452		
22	HEAD BLIND END		1	L_8BC		L_10BC			L_12BC		
23	HEAD GLAND END		1	L_8GC		L_10CC			L_12GC		
24	TRUNNION-INTERMEDIATE		1	L780		L7100			L7120		
25	CAP SCREW(GLAND BUSH, RETAINER)		4	25A1007		25A1008			25A1008		
27	LOCKWASHER (GL. BUSH, RETAINER)		4	9972		9972			9972		
38	GLAND BUSHING RETAINER		1	38L8		38L10			38L12		
** 40	PISTON WEAR RING		1	40H8037		40H107			40H127		
	SEAL KIT (PNEUMATIC)		1	KL80/13A	KL80/17A	KL80/20A	KL100/17A	KL100/20A	KL1220A	KL1225A	KL1230A

## NOTES:

Cushioning is supplied as standard on all cylinders unless ordered otherwise.

A partno having an underscore indicates a model letter code is required. See tables below.

Parts for a non-cushioned cylinder are the same as for cushioned except the check seals on the gland end remove the cushion sleeve.

Part numbers terminating in a dash must have the stroke value added immediately afterward.

\* Contact the factory for cushioning options on the gland end of the 1 1/2" bore (both rod sizes), and the 2" bore (1" and 1 3/8" only rod sizes). For these cylinders, the quantity of needle valves and needle valve seals must be halved.

\*\* These parts are in the seal kit.

\*\*\* Tie-rod part numbers for model LT only have a stroke value suffix, followed by a dash and then the required "X" value (see explanation following).

## HEAD PART NUMBER STRUCTURE:

- 1) SERIES - "L"
- 2) Use table (to right) to select head mounting style.
- 3) BORE eg 3-1/4" bore use 32, 4" bore use 40
- 4) LOCATION: G=Glnd or Rod end.
- 5) CUSHIONED = "C"
- (All heads are manufactured as cushioned.)

eg. Cyl. Model "LRS" 3-1/4" Bore, Cushioned  
Gland end head "LC32GC"  
Blind end head "LR32GC"

Note: if there is a Piston Rod Extension, the X1 value in the Tie-Rod Part Number

is reduced equally. For the above example with a 1" Rod Ext'n, 8LTC255-8.5 would become 8LTC255-8.4

## ROD PART NUMBER STRUCTURE:

- 1) COMPONENT NO - "4"
- 2) SERIES - "L"
- 3) THE CYLINDER BORE eg 3-1/4" bore use 32, 4" bore use 40
- 4) ROD SIZE 2 digits long as follows:  
eg. 1-3/4" rod = 17, 1" rod = 10, 5/8" rod = 06
- 5) OPTIONS: "CC"=Ctread, "F"=Female thread,  
"U"=Rod Extension for thicker Mg. Flange Plate(LR and LRS only)
- 6) STROKE VALUE, (to be preceded by a dash "-")  
eg. 7"stroke" - 7"

eg. 3-1/4" bore 1-3/8" rod, 8" stroke; "4L3213-8"  
eg. 4" bore 1" rod, CC thread, 8" stroke; "4L4010CC-8"  
Note: all piston rods are made cushioned.

## TIE-ROD PART NUMBER STRUCTURE:

- 1) COMPONENT NO - "8"
- 2) SERIES - "L"
- 3) CYL. MODEL - use table to right to select letter code  
Note: some cyl. models use a common code.
- 4) ROD SIZE - FOR LT MODEL ONLY "A", "B" or "C"  
A = R1 Rod size, B = R2, and C = Rod 3.
- 5) CYLINDER BORE (2 digits) ie. 20 = 2" bore
- 6) TIE-ROD DIA. in 16ths of an inch  
ie. 5 = 5/16" 12 = 3/4"
- 7) STROKE VALUE, preceded by a dash. For Models LT only.
- 8) X1 DIMENSION, preceded by a dash. For Models LT only.  
eg. 4" bore, model LTB, 1 3/8" rod, 8" stroke; 8L40-12
- 9) Tie-rod part numbers for model LT only have a stroke value suffix, followed by a dash and then the required "X" value (see explanation following).

CYLINDER MODELS	LETTER CODE
LNA	A
LNB,LNC	B
LC,LE,LW	C
LD	D
LF,LTR,LTBL,NM	F
LCH	H
LMP,LBS	P
LR,LRS	R
LT	T

## Cylinder Developed Force

BORE	ROD DIA.	DEVELOPED FORCE (lbs) @ DIFFERENTIAL PRESSURE (psi)											
		60		80		100		150		200		250	
		PUSH	PULL	PUSH	PULL	PUSH	PULL	PUSH	PULL	PUSH	PULL	PUSH	PULL
1 1/2	5/8	106	88	141	117	177	146	265	219	353	292	442	365
	1	106	59	141	79	177	98	265	147	353	196	442	245
	5/8	188	170	251	227	314	283	471	425	628	567	785	709
2	1	188	141	251	188	314	236	471	353	628	471	785	589
	1 3/8	188	99	251	133	314	166	471	249	628	331	785	414
	5/8	295	276	393	368	491	460	736	690	982	920	1227	1150
2 1/2	1	295	247	393	330	491	412	736	619	982	825	1227	1031
	1 3/8	295	205	393	274	491	342	736	514	982	685	1227	856
	1	498	479	664	639	830	799	1244	1198	1659	1598	2074	1997
3 1/4	1 3/8	498	451	664	601	830	751	1244	1127	1659	1502	2074	1878
	1 3/4	498	409	664	545	830	681	1244	1022	1659	1362	2074	1703
	1	754	707	1005	942	1257	1178	1885	1767	2513	2356	3142	2945
4	1 3/8	754	665	1005	887	1257	1108	1885	1662	2513	2216	3142	2770
	1 3/4	754	610	1005	813	1257	1016	1885	1524	2513	2032	3142	2540
	1	1178	1131	1571	1508	1963	1885	2945	2827	3927	3770	4909	4712
5	1 3/8	1178	1089	1571	1452	1963	1815	2945	2723	3927	3630	4909	4538
	1 3/4	1178	1034	1571	1378	1963	1723	2945	2584	3927	3446	4909	4307
	1 3/8	1696	1607	2262	2143	2827	2679	4241	4018	5655	5358	7069	6697
6	1 3/4	1696	1552	2262	2070	2827	2587	4241	3880	5655	5174	7069	6467
	2	1696	1508	2262	2011	2827	2513	4241	3770	5655	5027	7069	6283
	1 3/8	3016	2927	4021	3902	5027	4878	7540	7317	10053	9756	12566	12195
8	1 3/4	3016	2872	4021	3829	5027	4786	7540	7179	10053	9572	12566	11965
	2	3016	2827	4021	3770	5027	4712	7540	7069	10053	9425	12566	11781
	1 3/4	4712	4568	6283	6091	7854	7613	11781	11420	15708	15227	19635	19034
10	2	4712	4524	6283	6032	7854	7540	11781	11310	15708	15080	19635	18850
	2 1/2	4712	4418	6283	5890	7854	7363	11781	11045	15708	14726	19635	18408
	2	6786	6597	9048	8796	11310	10996	16965	16493	22619	21991	28274	27489
12	2 1/2	6786	6491	9048	8655	11310	10819	16965	16228	22619	21638	28274	27047
	3	6786	6362	9048	8482	11310	10603	16965	15904	22619	21206	28274	26507

### Published Design Data

Westcoast Cylinders Inc. reserves the right to change specifications and other information included in this catalogue without notice. All information, data and dimension tables in this catalogue have been carefully compiled and thoroughly checked. However, no responsibility for possible errors or omissions can be assumed.

Westcoast Cylinders Inc. warranties the material and workmanship of our cylinders for one full year when used under normal conditions, subject to factory inspection. WCI will repair or replace, at no cost for defective parts or cylinders. WCI will not incur expenses incurred in the field, pertaining to such repairs or replacements except upon written authority. For a complete statement of terms and warranty contact Westcoast Cylinders Inc.

### Warning

These products are intended for industrial use only. Do not use these products in applications where the pressure and temperature exceeds the values listed below.

Through misuse, age or malfunction, components used in fluid power systems can fail. A designer utilizing these products must consider all modes of failure when designing machines and provide safeguards or warn the end user of possible modes of failure.

### Cylinder Pressure and Temperature Ratings

L-Series cylinders are rated to 250 psig pneumatic pressure.

Temperature ratings for cylinders are limited to the maximum published temperature range of the least resistant seal component. In most cases that would be the standard buna-n o-ring seals. For higher temperatures specify a high temperature seal such as Viton. Buna-N temperature ratings: -30°F to 200°F (-34°C to 93°C).

### Bearing Load

Side loads on piston rods should be kept to a minimum to obtain maximum life from the cylinder gland bushing. To accomplish this, cylinders should not be used as an equipment support when mounted horizontally.

### Breakaway Pressure

Cylinder breakaway pressures vary between 5 and 10 psi depending on the bore size and mounting angle. Breakaway pressures will reduce after a break-in period.

### Cylinder Sizing

An air cylinder must generate sufficient force to move a load and overcome friction losses. System pressure losses must also be considered. The Cylinder Developed Force Table does not take into account friction or pressure losses. In addition, an air cylinder must be overpowered due to the compressibility of air. Therefore, the following general guidelines apply for sizing an air cylinder when using theoretical cylinder developed force values:

Multiply your load by one of the load factors below to get effective load.


Application	Load factor
Normal Speed	1.25
Intermediate Speed	1.5
High Speed	2

**Load x Load factor = Effective load**

Typically, pneumatic cylinder applications require flow controls to limit cylinder speeds. Flow control is done by controlling the flow of air as it exits the cylinder. This is done to ensure accurate cylinder speeds under all loads. The flow controls however do affect cylinder performance by maintaining back pressure on the piston. As a general rule, allow 20 psi pressure loss through flow control for good speed regulation.

**System pressure – 20 psi = Effective pressure**

SPECIFYING AN "X" IN ANY FIELD REQUIRES AN EXPLANATION IN THE SPECIAL NOTES FIELD.



Westcoast Cylinders Inc.

225 Edworthy Way  
New Westminster BC

## EXAMPLE "L4C12.188A1A1A1A"

\*Contact Factory for mounting dimensions

An "X" in any field requires an explanation in special notes.

Consult factory for options not shown.